

No Additional Safety Bollards Needed - Saves You \$500-\$700 Per Station - Housing is built with rugged, ¼” aluminum that’s weatherproof and corrosion resistant (bottom 1/3 of housing can be filled with concrete, eliminating the need for protective bollards).

Basic Equipment Details

Type of Mount	Pole Mount
Number of Ports	Dual
Intended Installation Setting	<ul style="list-style-type: none"> • Public • Workplace • Multi-Unit Dwelling
Networking Capability	Networked
Indicate whether the equipment uses an open standard protocol as a basic framework for purposes of network interoperability and for communication with the network services provider, and specify the protocol (such as OCPP)	Yes, OCPP 1.6 J Compatible
Network providers used to date	EvGateway
Input Power (kW AC)	208-240VAC 60Hz.@ 40A x 1.
Rated Output Power (kW AC)	7.2 KW
Can the equipment split power between multiple ports?	No
Dimensions (HxWxD, in inches)	Pole/Wall Mount: 54" H X 7" W
Charging cable length (in feet)	18
Operating temperature range	-30° to +130°F (-35° to +55°C)
Is the equipment ENERGY STAR® certified?	Yes
If no, do you have a Partnership Agreement with Energy Star?	
Does the equipment have a display screen?	Yes - LCD
Method(s) of Payment Accepted	<ul style="list-style-type: none"> • Network RFID Tag • Mobile Phone App
How do customers purchase the equipment?	<ul style="list-style-type: none"> • From the Manufacturer • From Network provider(s) • From 3rd party distributors
Warranty Duration (months)	24 Months

Special Features Included in the Equipment

- N/A

Optional Accessories

- Cord management system
- Cellular modems

Optional Services

- Data Collection Services
- Technical Support
- 24x7 Driver Support
- Extended Warranty
- Maintenance Services

Distributors

Tellus Power Green

www.telluspower.com

Divina Azures | 949-945-3000 | divina@telluspowergreen.com

QWIK Charge

www.qwikcharge.com

Andrew Richard | 770-823-7973 | andrew.richard@qwikcharge.com

EvGateway

www.evgateway.com

Laura Pichardo | 949-945-2000 | laura@evgateway.com